

Wiring diagram

SUB-D15F-HD

TxD .2
RxD .3
GND .4
RTS .6
CTS .10

AWG32
AWG32
AWG28
AWG32
AWG32

Green
Green/Black
Red
Blue
Light Blue

SUB-D9F

2. TxD
3. RxD
5. GND
7. RTS
8. CTS

Black

OUT_0 .7
IN_0 .8
IN_1 .9
VDC .5
OUT_1 .11
COM_OUT .12
OUT_STROBE .13

AWG28
AWG28
AWG28
AWG28
AWG28
AWG28
AWG28

Blue/White
White
White/Black
Brown/White
Light Blue/Black
Light Blue/Yellow
Light Blue/Green

Flying lead
Flying lead
Flying lead
Flying lead
Flying lead
Flying lead
Flying lead

Shield .Shell

Transparent

Flying lead